

## 8-Port 100Mbps+ 1-Combo Port

# Switch with 8-Port Passive PoE NC-PUS091GF-24V

#### **Features**:

- With 8 PoE ports, transfers data and power on one single cable
- > 1\*1000M combo(RJ45+SFP) Uplink port
- Working with 24V Passive PoE PDs, expands SMB and office network




www.nc-link.cn

Power Supply: 120W

#### Description

NC-PUS091FD-24V, 8GE+1SFP+1GE PoE Switch is right for remote 100M wireless cabling and HD monitoring network. Besides with access of high performance, it provides 8 10/100/1000M Base-T Ethernet ports and 1 extra independent 1000Base-X Gigabit SFP and Ethernet port. Ports 1~8 support 24V Passive PoE standard; supply electricity and transmit data at the same time to AP, IP Camera or IP Phone via Cat.5 twisted-pair cables. In addition to these, it provides stronger safety protection system. To sum up, 8FE+1SFP+1GE PoE Switch is an ideal and safe switch for easy use.

1




### 4 Specification

Hardware	
Interface	8 10/100/1000Mbps RJ45 Ports 1*10/100/1000Mbps RJ45/SFP Port AUTO Negotiation/AUTO MDI/MDIX
Network Media	10BASE-T: UTP category 3, 4, 5 cable (maximum 100m) EIA/TIA-568 100Ω STP (maximum 100m) 100BASE-TX: UTP category 5, 5e cable (maximum 100m) 1000BASE-TX: UTP category 5e,6 cable (maximum 100m) EIA/TIA-568 100Ω STP (maximum 100m)
PoE Ports (RJ45)	Standard: 24V Passive PoE PoE Ports: Port1- Port8 Power Supply:120W
Backbound Bandwidth	5.6Gbps
Power Supply	100-240VAC, 50/60Hz
Dimensions (L xW x H )	230mm*170mm*44mm

#### SOFTWARE

Transfer Method	Store and Forward
MAC Address Table	8К
Advanced Functions	Compatible With 24V Passive PoE PDs
	Priority Function
	Mac Address Auto-Learning And Auto-Aging
	IEEE802.3x Flow Control For Full-Duplex Mode And
	Backpressure For Half-Duplex Mode

2



Others	
Environment	Operating Temperature: 0℃~60℃ (32°F~140°F); Storage Temperature: -40℃~70℃ (-40°F~158°F); Operating Humidity: 10%~90% non-condensing; Storage Humidity: 5%~90% non-condensing
Package	8-Port 100Mbps+ 2-Combo Port Switch with 8-Port PoE 48V/3A Power Adapter User Guide
System Requirements	Microsoft <sup>®</sup> Windows 8, Windows 7,98SE, NT, 2000, XP, Vista™ , MAC <sup>®</sup> OS, N48VetWare <sup>®</sup> , UNIX <sup>®</sup> or Linux.

